



TruLink® TV to PC Converter

- Convert TV signals, Composite Video, S-Video, Component Video and Cable TV, to a VGA PC video signal
- Audio pass-through to support computer speakers
- IR remote control included
- One year warranty



Specifications: TruLink® TV to PC Converter

Audio/Video Specifications

Audio/Video inputs:	Composite Video S-Video Component Video F-type (Cable TV) VGA (HD15) 3.5mm Stereo Audio Dual RCA Stereo Audio
Audio/Video outputs:	VGA Composite Video 3.5mm Stereo Audio
Cable TV receivable channel range:	DS1 - 57ch Z1 - 38ch (470mHz full TV)
Frame frequency:	60/75Hz
Line frequency range:	31KHz - 80KHz
Cable TV input:	75Ω unbalanced

Power Adapter Specifications

Power input:	100~240V AC 60/50Hz, 0.2A
Power output:	5V DC, 1.0A
Power adapter cable length:	5ft
Power pin diameter:	5.5mm
Center pin polarity:	Positive

Physical Specifications

Weight:	1.00lb
Dimensions (HxWxD):	1.13 x 6.88 x 4.62in

Part Number	Description	Weight
41000	TruLink® TV to PC Converter	1.00lb

